



## SE-908 FPE FLOURESCENT TUBE SELF-CONTAINED EMERGENCY KELUAR SIGN

### Technical Data

Mode of Operation	: Sustained.
Input Voltage	: 240V $\pm$ 10%, 50Hz
Battery	: Hi-Temp. Nickel Cadmium Battery.
Charging Current	: 80mA (Nominal).
Lamp Used	: 2 x 8 Watt Fluorescent Tube
Operating Temperature	: 0°C to 60°C
Charger	: Fully Automatic Constant Current. Solid-State Electronics Provide High Reliability with Trickle Charge-Facility.
Indication	: Red L.E.D. "On" Indicates Charging. Equipped with Push Test-Switch to Simulate Power Failure.
Backup Time	: 3 Hours Duration.
Construction	: Injection Moulded Fire-Retardant ABS Polyester Casing with Side Knockout Cable Entry.
Weight	: $\pm$ 1.4kg
#Warranty	: 5 Years.
Compliance	: Malaysia Standards MS-983, IP-20.

Dimension in mm  
Tolerance:  $\pm$  0.03 mm  
**Wall Mounting**

