



- Auto range and manual range selector provided. (with range hold feature)
- Continuity test buzzer.
- Diode test feature.
- 3200 counts with bargraph.
- Resistance range provides audible continuity test.
- Automatically turns power off in about 10 minutes to conserve battery life.
- Direct current measurement up to 10A AC and DC.

DC V	300mV/3/30/300/1000V (Input Impedance 10M Ω)
	$\pm 0.5\%rdg \pm 2dgt$ (300mV)
	$\pm 1\%rdg \pm 2dgt$ (3/30/300V)
	$\pm 1\%rdg \pm 4dgt$ (1000V)
AC V	3/30/300/750V (Input Impedance 10M Ω) $\pm 1.2\%rdg \pm 4dgt$
DC A	300/3000 μ A/30/300mA/10A
	$\pm 1.5\%rdg \pm 2dgt$ (300 μ A/30mA)
	$\pm 2\%rdg \pm 2dgt$ (3000 μ A/300mA/10A)
AC A	300/3000 μ A/30/300mA/10A
	$\pm 2\%rdg \pm 5dgt$ (300/3000 μ A/30/300mA)
	$\pm 2.5\%rdg \pm 5dgt$ (10A)
Ω	300 Ω /3/30/300k Ω /3/30M Ω
	$\pm 1\%rdg \pm 2dgt$ (300 Ω /3/30/300k Ω)
	$\pm 2\%rdg \pm 2dgt$ (3M Ω)
	$\pm 3.5\%rdg \pm 2dgt$ (30M Ω)
Diode Test	2V Release Voltage: Approx. 1.3V
Continuity buzzer	300 Ω (Buzzer sounds below 20 Ω)
Withstand Voltage	5500V AC for 1 minute
Power Source	R6 (AA) (1.5V) \times 2
Dimensions	167.5(L) \times 78(W) \times 37.5(D)mm
Weight	250g approx.
Accessories	7066 (Test Leads)
	8922 (0.5A/250V fuse) \times 2
	8921 (10A/250V fuse) \times 1
	9086 (Carrying Case)
	R6 (AA) \times 2
	Instruction Manual