



- Equipped to measure both AC and DC current with transformer jaws of large diameter.
- Can measure AC and DC currents up to 2000A.
- Output terminal for connection to recorders.

CE

CAT IV 600V
Φ55
MAX 2000A
DC AC A
DC AC V
Ω
••••
DATA HOLD
OUT PUT

AUTO POWER SAVE

AC A	400A/2000A (0 - 1000A) ±1.5%rdg±2dgt [50/60Hz] ±3%rdg±4dgt [40 - 500Hz] ±5%rdg±4dgt [500Hz - 1kHz] 2000A (1001 - 2000A) ±3%rdg±2dgt [50/60Hz]
DC A	400/2000A ±1.5%rdg±2dgt
AC V	400/750V ±1.5%rdg±2dgt [50/60Hz] ±1.5%rdg±4dgt [40Hz - 1kHz]
DC V	400/1000V ±1%rdg±2dgt
Ω	400/4000Ω ±1.5%rdg±2dgt
Continuity buzzer	buzzer sounds below 50±35Ω
Conductor size	Ø55mm max.
Frequency response	40Hz - 1kHz
Output	Recorder : DC400mV against AC/DC400A DC200mV against AC/DC2000A
Safety Standard	IEC 61010-1 CAT IV 600V , CAT III 1000V IEC 61010-031 IEC 61010-2-032
Power source	R6 (AA) (1.5V) × 2
Dimensions	250(L) × 105(W) × 49(D)mm
Weight	530g approx.
Included Accessories	7107A (Test leads) 9094 (Carrying Case) R6 (AA) × 2 Instruction Manual
Optional Accessories	7256 (Output cord)